

## RNGFAP12DMMKLC5

Article Number: 904-00795

RapidNet Fiber Adapter Panel 12 DUP, MM, LC Orange 1/pkg



### Base Data

Local Order Number RNGFAP12DMMKLC5

Type RNGFAP

- Features and Benefits**
- Ideal for installations with limited access or restricted space.
  - Available in in 6 or 12 hole configuration.
  - Allows ruggedized fan-outs to be presented in RapidNet Panels.
  - Fits into a standard RapidNet Panel.
  - Supports a maximum of 1152 fibers in 1U of space.

**Product Description** The RapidNet Fiber Adapter Panel is designed to allow the RapidNet solution to be used in areas with limited access or restricted space, where a RapidNet Cassette cannot be used. Panels are pre-loaded with adapters, which allow ruggedized fan-outs to be presented in RapidNet panels - offering a maximum of 288 fibers in a single adapter, or 1152 fibers in 1U of space.

**Technical Description** The RapidNet Fiber Adapter Panel is supplied in a 12 or 6 hole configuration. Panels are customized with a choice of MTP, SC or LC adapters. Panels can be used in any RapidNet panel, but are recommended for use with the RapidNet Distribution Chassis or Rear Cable Management Panel, to provide rear cable management and protection for the fan-out cable. All fiber adapters and connectors comply with the latest published version of IEC874-14, ensuring interoperability.

**Short Description** RapidNet Fiber Adapter Panel 12 DUP, MM, LC Orange 1/pkg

### Product Dimensions

Length L (imperial) 2.1 "

Length L (metric) 53.75 mm

Fiber Count 24

Width W (imperial) 4.0 "

Width W (metric) 102.7 mm

Height H (imperial) 1.1 "

Height H (metric) 27.8 mm

### Logistics and Packaging

Quantity per box

Package Quantity 1

Weight (imperial) 4 oz

Weight (Metric) 113.4 g

### Material and Specifications

Material Plastic

Material Shortcut Plastic

